

## HR-IB120 USB MINI

INVERTER DC/AC

12Vdc/230Vac

## **Description**

Particularly suitable for briefcases thanks to it extra flat shape, ideal for storage in the glove compartment of your car. Available USB power (5V), which puts it in the forefront of new technologies. Allows you to upload your digital camera, MP3 player, laptop, cell phone ... without having to resort to a multiple adapters. Their mini size makes it possible take it to any place without having to leave at the sight of curious / thieves etc.



## **Technical characteristics**

General specifications	
Wave shape	Modified sine wave
Output Voltage	230 Vca
Output frecuency	50Hz
Maximum power (continious way)	120W
Voltage input range	10-15Vdc
Low battery alarm	10 Vdc
Shutdown for low battery	9 Vdc
Shut down for high battery voltage	15Vdc
Short-circuit protection	Automatically cut output voltage
Protections	Overload and Overheating
USB output	5V- 500mA

## **Accessories**

- Connection cable for car cigarette lighter socket and airplane connector